

CE-178A

VESA 75/100 Articulating TV Mount

- Articulating Arm Wall Mount Bracket
- Articulating Arm Extends to 17"
- VESA 75mm and VESA 100mm Compliant
- 3-Axis Adjustment
- VESA Mounting Hardware Included
- Steel and ABS Construction
- Adjustable Ball Joints with Wrench
- Recommended for use with TRU-Vu Monitors up to 22 lbs.
- UL Listed
- Also Available in Beige



Tru-Vu Articulating TV Mount extends to 17" and is VESA 75mm and VESA 100mm Compliant. It is UL Listed, and has 3-Axis adjustment to position the monitor perfectly every time. This VESA wall mount includes Mounting Hardware and VESA screws. We recommend this articulating TV mount arm for use with TRU-Vu Monitors up to 35 lbs. Great for small and touch screens. Learn more about [VESA](#).

How Do I Mount My TRU-Vu Monitor?

- Many of our monitors are supplied with a tabletop base. (See the respective data sheet) If not, they are available for purchase.
- We offer optional tabletop bases and VESA wall mount brackets for all monitors. See our [Mounting Brackets and Bases](#) for more details and available styles.
- All TRU-Vu monitors 8.4" and larger have 4 industry-standard VESA screw holes for mounting. These are arranged in a square pattern, 75 x 75 mm, 100 x 100 mm or 200 x 200 mm center-to-center. Monitors from 8.4" to 32" use M4 screws. They should sink into the monitor no more than 6-7 mm. Monitors 42" and larger use M6 screws. They should sink into the monitor no more than 7 mm. VESA mount hole patterns range from 100 x 100 mm to 200 x 200 mm.

DIMENSIONS (MM)

